

インダイレクトモード		
Command	Code	Parameter
MWRITE	42	P1
		P2
		.
MREAD	43	P1
		P2
		.
SYSTEMSET	40	P1
		P2
		P3
		P4
		P5
		P6
		P7
		P8
SLEEP IN	53	-
DISP ON/OFF	58	-
	59	P1
SCROLL	44	P1
		P2
		P3
		P4
		P5
		P6
		P7
		P8
		P9
		P10
CSRFORM	5D	P1
		P2
CSRDIR	4C	-
	4D	-
	4E	-
	4F	-
OVLAY	5B	P1
CGRAM ADR	5C	P1
		P2
HDOT SCR	5A	P1
CSRW	46	P1
		P2
CSRR	47	P1
		P2
GRAY SCALE	60	P1

ダイレクトモード	
Address	
0000h	
~	
7FFFh	
8000h	
8001h	
8002h	
8003h	
8004h	
8005h	
8006h	
8007h	
8008h	
8009h	
800Ah	
800Bh	
800Ch	
800Dh	
800Eh	
800Fh	
8010h	
8011h	
8012h	
8013h	
8014h	
8015h	
8016h	
8017h	
8017h	
8017h	
8017h	
8018h	
8019h	
801Ah	
801Bh	
801Ch	
801Dh	
801Eh	
801Fh	
8020h	
8021h	
~	
802Fh	
8030h	
~	
FFFFh	

内容							
7	6	5	4	3	2	1	0
Display RAM area							
0	0	IV	1	WS	M2	0	M0
WF	0	0	0	FX			
0	0	0	0	FY			
CR							
TCR							
LF							
APL							
APH							
0	0	0	0	0	0	0	Sleep
0	0	0	0	0	0	0	Display
FP5	FP4	FP3	FP2	FP1	FP0	FC1	FC0
SAD1L							
SAD1H							
SL1							
SAD2L							
SAD2H							
SL2							
SAD3L							
SAD3H							
SAD4L							
SAD4H							
0	0	0	0	CSRX			
CM	0	0	0	CSRY			
0	1	0	0	1	1	0	0
0	1	0	0	1	1	0	1
0	1	0	0	1	1	1	0
0	1	0	0	1	1	1	1
0	0	0	0	OV	DM	MX	
SAGL							
SAGH							
0	0	0	0	0	HSR		
CSRWR L							
CSRWR H							
CSRRL L							
CSRRL H							
0	0	0	0	0	0	GrayScale	
Reserved							
Not use							